

**Step 1.** Make sure you have settled any current open batch

**Step 2.** From the main menu (date/time/sale), press 'F2' & 'F4' at the same time.

**Step 3.** Key in the password: Press **1, Alpha, Alpha, 6, 6, 8, 3, 1,** and then press the green **Enter** key.

**Note:** Asterisks appear on the screen as the password is keyed in. However, pressing the **Alpha** key does not add an asterisk.

**Step 4.** Press **1** to select **Edit Parameters.**

**Step 5.** Press **1** for Group ID, and then press the green **Enter** key.

**Step 6.** Key in the password: Press **1, Alpha, Alpha, 6, 6, 8, 3, 1,** and then press the green **Enter** key.

**Step 7.** The **Terminal Mgr Edit G1 CONFIG.SYS** displays, press the green **Enter** key.

**Step 8.** Add first new new parameter (**\*DHEAP**)

1. Press **1** to select **New.**
2. Press **\*** and then an **\*** displays.
3. Press **3, Alpha** and then **\*D** displays.
4. Press **4, Alpha, Alpha** and then **\*DH** displays.
5. Press **3, Alpha, Alpha** and then **\*DHE** displays.
6. Press **2, Alpha** and then **\*DHEA** displays.
7. Press **7, Alpha** and then **\*DHEAP** displays.
8. Press the green **Enter** key.

**Step 9.** Press **0** for the value, and then press the green **Enter** key to save the new parameter.

**Step 10.** Add next new parameter (**#CZE**)

1. Press **1** to select **New.**
2. Press **#** and then an **#** displays.
3. Press **2, Alpha, Alpha, Alpha** and then **#C** displays.
4. Press **1, Alpha, Alpha** and then **#CZ** displays.
5. Press **3, Alpha, Alpha** and then **#CZE** displays.
6. Press the green **Enter** key.

**Step 11.** Press **1** for the value, and then press the green **Enter** key to save the new parameter.

**Step 12.** Press the red **Cancel** key.

**Step 13.** Press **3** to select **Restart.**